

Gigaset C470 IP

Simple
step-by-step
installation



SIEMENS

Warning:

Read the safety precautions and the user guide on the CD before use.

Explain their content and the potential hazards associated with using the telephone to your children.

- > Only use the mains adapters supplied, as indicated on the underside of the base station or charging cradle.
- > Only use the **recommended, rechargeable batteries**, i.e. never use a conventional (non-rechargeable) battery or other battery types as this could result in significant health risks and personal injury. For example, the outer casing of the batteries could be damaged or the batteries could explode. The phone could also malfunction or be damaged as a result of using batteries that are not of the recommended type.
- > Insert rechargeable batteries with the correct polarity, and use them in accordance with the user guide (polarity symbols are displayed in or on the handset's battery compartment).
- > Batteries should not be disposed of in general household waste. Observe the local waste disposal regulations, details of which can be obtained from your local authority or the dealer you purchased the product from.
- > The operation of medical appliances may be affected. Be aware of the technical conditions in your particular environment, e.g. doctor's surgery.
- > Do not hold the rear of the handset to your ear when it is ringing or when the handsfree function is activated. Otherwise you risk serious and permanent damage to your hearing. The handset may cause an unpleasant humming noise in hearing aids.
- > Do not install the base station or charging cradle in bathrooms or shower rooms. The handset, base station and charging cradle are not splashproof.
- > The charging cradle and base station are designed for use in enclosed dry rooms with a temperature range of +5°C to +45°C.
- > Do not use the phone in environments with a potential explosion hazard, e.g. paint shops.
- > Never expose the telephone to any of the following: heat sources, direct sunlight or other electrical appliances.
- > Protect your Gigaset from moisture, dust, corrosive liquids and vapours.
- > If you give your Gigaset to someone else, make sure you also give them the user guide.
- > Please remove faulty base stations from use or have them repaired by our Service Centre, as they could interfere with other wireless services.
- > All electrical and electronic equipment must be disposed of separately from general household waste using the sites designated by local authorities.




If a product displays this symbol of a crossed-out rubbish bin, the product is subject to European Directive 2002/96/EC.

The appropriate disposal and separate collection of used equipment serve to prevent potential harm to the environment and to health. They are a precondition for the re-use and recycling of used electrical and electronic equipment.

For further information on disposing of your used equipment, please contact your local authority, your refuse collection service or the dealer you purchased the product from.

Warning:

When the keypad lock is active, you cannot call emergency numbers.



- 1 Gigaset C470 IP base station
- 2 Mains adapter for connecting the base station to the mains power supply
- 3 Phone cord for connecting the base station to the fixed line network
- 4 Ethernet (LAN) cable for connecting the base station to the router (LAN/Internet)
- 5 Gigaset C47H handset
- 6 Two batteries for the handset (uncharged)
- 7 Battery compartment cover for the handset
- 8 Belt clip for the handset
- 9 Mains adapter for connecting the charging cradle to the mains power supply
- 10 Handset charging cradle
- 11 CD with the user guide for your Gigaset.

If the firmware for your base station is updated, the user guide will also be updated and made available for download on the Internet at www.gigaset.com.

**Display keys:**

Start function displayed to the left or right of the bottom display line

**Handsfree key:**

Switch between earpiece and handsfree mode (key lights up)

**Talk key:** accept call

After entering number: start dialling via VoIP/ fixed line network (press briefly/press and hold)

**Control key:**

Open directory (press down)

Open list of online directories (press and hold the bottom of the control key)

Scroll through menus (press up or down)

Navigate in text

**Message key:**

Open calls and messages lists

Flashes: new call, new message/firmware

**End call key, on/off key:**

End call, cancel function (press briefly)

Return to idle status (press and hold)


Switch handset on/off (press and hold)

**Fast access key** (press and hold):

Listen to messages on the network mailbox

*** key:** Ringer on/off (press and hold)**# key:** Keypad lock on/off (press and hold)**Recall/pause key** (fixed line network)

Open **call-by-call list** (fixed line network)



- 1 Preparing the handset: inserting the batteries
- 2 Connecting the charging cradle to the mains power supply and charging the batteries
- 3 Connecting the phone cord and power lead to the base station
- 4 Connecting the base station to the fixed line network and the mains power supply
- 5 To connect the base station to the Internet, first connect the base station to the router (connection via router and modem or via router with integrated modem)
- 6 PC in LAN (optional) for advanced configuration of the Gigaset C470 IP base station


1 Inserting the supplied batteries and closing the battery cover



- > Check the polarity when inserting the batteries (see symbols in or on the battery compartment).
- > Only use the recommended rechargeable batteries.


Once the batteries have been inserted, the handset switches on automatically.

- A** Insert the battery compartment cover into the notches at the top of the battery compartment.
- B** Then press the battery compartment cover until it clicks into place.




> The display is protected by a plastic film. Please remove the protective film!

2 Connecting the charging cradle and charging the batteries




> Observe the sequence (A, B)!



- > Place the handset in the charging cradle and wait until the batteries are fully charged.

- > Do not put the handset back in the charging cradle until the batteries are fully discharged through use.
- > After the first battery charge **and** discharge, you may place your handset in the charging cradle after every call.
- > The battery charging status is displayed in the idle display: (flat to full).

3 Connecting the phone cord and power lead to the base station




- A** Insert the phone cord into the lower connection socket at the rear of the base station.
- B** Insert the power lead of the mains adapter into the upper connection socket at the rear of the base station.
- C** Insert both cables into their respective cable recesses.


Only use the supplied phone cord and the supplied mains adapter.

4 Connecting the base station to the fixed line network and mains power supply


- A** Insert the phone cord into the fixed line network connection socket.
- B** **Then** insert the mains adapter into the mains socket.

Keep the mains adapter **plugged in at all times** for operation, as the phone does not work without a mains connection.



You can now use your phone to make calls via the fixed line network:
Enter the number using the handset, and then press and **hold** the talk key .


5 Connecting the base station with the router (Internet)



- A** Connect one Ethernet cable plug to the LAN socket at the side of the base station.
- B** Insert the second Ethernet cable plug into a LAN socket on the router.

Use the Ethernet cable supplied.

As soon as the cable connecting the phone and router is plugged in, the key lights up on the front of the base station (paging key).



6 Connecting the PC to the router (optional)

Further configuration of the base station can be performed via a PC in the LAN.

> Connect the PC network connection to a free LAN socket on your router.

> The procedure below requires that your phone is automatically assigned an IP address by the router (i.e. DHCP is enabled on router and phone).

In **exceptional cases** (e.g. if DHCP is not enabled on the router) you will have to assign a static IP address to the base station for LAN access. You must enter this IP address on the handset before carrying out the following steps. Further information can be found in the user guide on the enclosed CD.

The following handset menu can be used to make the entry:

 → Settings → Base → Local Network → (Enter system PIN)

> VoIP should be set as the default line for your phone (default setting). You will then immediately receive corresponding messages if a connection to the provider's VoIP server cannot be established due to incorrect/incomplete data.

Instead of using the following procedure, you can also enter the VoIP access data using your PC (steps **7** to **11**):

- > Launch the Web browser on your PC.
- > Enter the URL **http://www.Gigaset-config.com** in the address field of the Web browser and press the return key.

You are connected to your base station's Web configurator. You will find a description of this in the user guide on the enclosed CD.

Precondition for the following steps:

Before you can use VoIP to phone any other subscribers on the Internet, the fixed line network or the mobile phone network, you need a VoIP account.

- > Set up a VoIP account with a VoIP provider.
- > Have the VoIP account data you received from your VoIP provider to hand.


You will need:

- > Your registration name (login ID), your password and, if applicable (provider-dependent), a user name (often this is your VoIP phone number).

Or


- > Your personal auto-configuration code (activation code), if your provider supports "automatic configuration".

7 Starting the configuration process

When your handset is sufficiently charged (approx. 20 minutes after you have placed it in the charging cradle), the message key  on the handset flashes.




- > Press the message key  on the handset.


If "Update firmware?" is shown in the display, updated firmware is already available for your phone. Press the right-hand display key **Yes**. The new firmware is loaded. This takes approx. 3 minutes. The message key  will now flash again.

- > Press the message key  to start configuration.

8 Starting the connection assistant, entering the PIN



- > Press the key below **Yes** on the display (= right display key).



- > Using the number keys, enter the base station's system PIN. By default, the PIN is "0000".
- > Press the right-hand display key **OK**.

If the connection assistant does not start properly, you can start it via the menu:




→ Settings → Telephony → Connection Assist.

Provided that your phone is set for auto-configuration (default setting), you will see the following display. Otherwise go to **10**.

If you have received a **registration name/password** and, if applicable, a user name:


- > Press the left-hand display key **No**.
- > For more information, see **10**.



If you have received an **auto-configuration code**:

- > Press the right-hand display key **Yes**.
- > For more information, see **9**.

9 Entering an auto-configuration code



- > Enter your auto-configuration code using the keypad (max. 32 characters).
- > Press the right-hand display key **OK**.


All data necessary for VoIP telephony is loaded directly from the Internet to your phone.


Following successful download, Saved is shown in the display.


Proceed as described under **12**.

10 Selecting a provider and loading provider data to the base station





- > Select your country with the control key  (press down arrow).
- > Press the display key **OK**.



- > Select your provider with the control key  (press down arrow).
- > Press the display key **OK**.

If your provider does not appear in the list, you have the following options:


- > Press the left display key  twice and continue as described in **11**.
However, you can only make a call via VoIP once you have completed the provider details using the Web configurator. Your VoIP provider will supply you with this data.
- > Exit the connection assistant by holding the end call key  and entering the provider and VoIP account details via the Web configurator.

You will find more detailed information about this in the user guide on the enclosed CD.




11 Entering VoIP account data



- > Using the number keys, enter the authentication name (user identification) that you received from your VoIP provider. This entry is case-sensitive.
- > Press the right display key **OK**.



- > Using the number keys, enter the authentication password that you received from your provider. This entry is case-sensitive.
- > Press the right display key **OK**.

- > To switch between upper and lower case and digits, press the  key (several times if necessary).
 - > Characters entered incorrectly can be deleted using the left display key . The character to the left of the cursor will be deleted.
 - > You can navigate within the input field using the control key  (press right/left).
- > Depending on your provider, you may be prompted to enter a user name. Enter it as described above.


If you have made all the required entries, the message "Connection data complete" will appear briefly on the display.

You can enter five additional VoIP accounts (VoIP phone numbers) via your base station's Web configurator. You will find more information in the user guide on the enclosed CD.

12 Completing the VoIP settings

The handset switches to idle status. The idle display status is displayed.

If all the VoIP settings are correct and if the phone can establish a connection to the VoIP server, the internal name of the handset will be displayed: (example)



You can now use your phone to make calls via the fixed line network and the Internet! Callers can contact you on your fixed line network number, your Gigaset.net number or your VoIP number!

To ensure that you can always be reached via the Internet, the router must be permanently connected to the Internet.

Testing your VoIP connection

If a message is displayed when you are trying to make a call via VoIP, you can check the base station's connection to the Internet by e.g. calling the Gigaset.net echo service:

> Enter one of the following phone numbers:

12341#9 (English)


12342#9 (Dutch)

12343#9 (Italian)

12344#9 (French)

12345#9 (German)

12346#9 (Spanish)

> Press the talk key .

> When prompted, speak into the microphone on the handset.

If you hear your own voice, your base station is connected to the Internet.

If you do not hear your voice, check your phone and router settings.






In the user guide on the enclosed CD, you will find detailed information about setting up and operating your phone, as well as possible solutions to frequently asked questions and common problems.


Entering your name in the Gigaset.net directory

Gigaset.net* is a VoIP service provided by Gigaset Communications GmbH, which you can use to make **free calls** to other Gigaset VoIP users.

The **first** time you open the Gigaset.net directory, complete the following steps and an entry will be created in the Gigaset.net directory for you:

- > Press down on the control key  to open the handset directory.
- > Press down on the control key  repeatedly until Gigaset.net is selected.
- > Press the green talk key .

A connection to the Gigaset.net online directory is established. You will see the following display:



- > Press the right-hand display key **Yes**.



- > Using the number keys, enter the name that you would like to be listed under in the Gigaset.net directory.
- > Press the right display key **OK**.



If an entry with this name already exists, the message "Nickname exists! Please change." will be displayed. You will be prompted to enter a name again.

If an entry in the Gigaset.net directory is successful, the message "Your user name is successfully added to Gigaset.net!" will be shown.

* Exclusion of liability

Gigaset.net is a voluntary service provided by Gigaset Communications GmbH with no liability or guarantee for the availability of the network. This service can be terminated at any time with a notice period of three months.

Making calls

- > Enter a phone number using your handset's number keys.
Please note that, even with local calls, you must always dial the area code for calls via VoIP (provider-dependent).
 - > **Briefly** press the talk key  if you want to make a call via **VoIP**.
- Or
- > Press and **hold** the talk key  if you want to make a call via the **fixed line network**.

When making a call via VoIP, IP is shown in the top right-hand corner of the display.

We offer you support that is fast and tailored to your specific needs!

Our Online Support on the Internet can be reached any time from anywhere.

www.gigaset.com/customercare

It provides you with 24/7 support for all our products. It also provides a list of FAQs and answers plus user guides and current software updates (if available for the product) for you to download.

You will also find frequently asked questions and answers in the detailed user guide on the enclosed CD or in the Internet at www.gigaset.com.

For fast and dependable assistance with any repairs or guarantee/warranty claims, contact our Customer Care Line.

Greece 801 1000 500 (0,026 Euro)

Please have your proof of purchase ready when calling.

Replacement or repair services are not offered in countries where our product is not sold by authorised dealers.

Please address any questions about DSL access and VoIP access to the respective service provider.

Authorisation

This device is designed for the analogic telephone connection in the greek telephone net.


Voice over IP telephony is possible with an additional modem via the LAN interface.

Gigaset Communications GmbH hereby declares that the phone described in this user guide is in compliance with the essential requirements and other relevant provisions of European Directive 1999/5/EC (R&TTE).

If you require a copy of the original, visit the **website**:

www.gigaset.com/docs.

CE 0682



A31008 - M1916 - T101 - 2 - 8U43

Issued by

Gigaset Communications GmbH, Schlavenhorst 66, D-46395 Bocholt
Gigaset Communications GmbH is a trademark licensee of Siemens AG

© Gigaset Communications GmbH 2009

All rights reserved. Subject to availability. Rights of modifications reserved.

www.gigaset.com